

TVC-32

convert to 64x16 (TVC-64)

Break Line from:			
IC	Pin	To IC	Pin
32	7	14	2,12
17	3	18	4
17	2	20	4
17	6	11,18	1,3
17	7	13	2
21	3	14,11	1,3
28	11,10	10	3
28	5	10	2
28	2	10	6
8	14	10	7
1-7	14	ground	

connect Line from				
IC	Pin	To	IC	Pin
17	3	-	14,11	2,12
17	2	-	18	4
17	6	-	20	4
17	7	-	11,18	1,3
21	3	-	13	2
21	2	-	14,11	1,3
28	11,10	-	21	3
28	5	-	10	3
28	2	-	10	2
8	14	-	10	6
8	11	-	10	7
8	9	-	1-7	14

Replace 5.990 MHz crystal with 11.980 MHz crystal.

u

v